

## Meridian G Series Players RS232 Commands

The RS232 interface can be operated from any terminal program with the following settings:  
 9600 bits per second, 8 data bits, 1 stop bit, no parity, no flow control.

G Series players echo all characters to the terminal program.

A carriage return causes the command to be executed.

Backspace deletes the last character.

A # symbol following a command represents a number.

All commands are case sensitive.

DVD players output aspect ratio information when the video stream changes; for example, SCREEN: 16x9.

The following tables list the commands available and show examples of the messages returned.

### Source commands

Command	Action	Example output
CD	CD source	CD 65
RD	Radio source	Radio 65
DV	DVD source	DVD 65
AX	Aux source	Aux 65
DC	Disc source	Disc 65
TA	Tape source	Tape 65
TV	TV source	TV 65
CB	Cable source	Cable 65
SA	Satellite source	Sat 65
V1	VCR1 source	VCR1 65
V2	VCR2 source	VCR2 65
GA	Game source	Game 65

### Volume commands

Command	Action	Example output
VP	Volume up	CD 66
vp	Function + volume up	
VM	Volume down	CD 64
vm	Function + volume down	
VN#	Go to volume number #	CD 65
MU	Toggle mute	Mute
mu	Function + mute	

### Other MSR Plus commands

Command	Action	Example output
SB	Standby	.
MR	Menu right	
mr	Function + menu right	
ML	Menu left	
ml	Function + menu left	
MP	Menu up	
mp	Function + menu up	
MM	Menu down	
mm	Function + menu down	
PL	Play	1 0:07
ST	Stop	13 --:--
PS	Pause	PS 0:13
RP	Repeat	Repeat track
rp	Function + repeat	Repeat A-B
NE	Next	Track 2
PR	Previous	Track 2
DI	Display	2 3:13
di	Function + display	
SR	Store	Store 12
sr	Function + store	
CL	Clear	Clear 4
cl	Function + clear	
DP	DSP	Trifield
FF	Fast forward	>> 0:21
FB	Fast back	<< 0:15
N0 – N9	0 – 9	Track 6
OP	Open	Open
#B	# button	Track -
NP	Next page	
PP	Previous page	
TM	Top menu	
SL	Slow	1 0:00:07
BA	Band	108.0 MHz
AU	Audio stream	
SU	Subtitle (on/off)	
su	Function + subtitle (select)	
OS	OSD	

RC	Record	
AN	Angle	
AB	A-B repeat	Repeat A-B
PH	Phase	Phase +
TB	T button (MSR 3)	Track -
CH	Chapter	
SE	Set up	OSD Setup
ME	Menu	SCREEN: 4x3
RT	Return	
EN	Enter	
TI	Title	
RE	Red button	X= 0 Y= 0
GR	Green button	Input 16x9
YE	Yellow button	
BL	Blue button	

### Playback commands

Command	Action	Example output
GTT #	Go to title number	1 0:00:00
GCH #	Go to chapter number	2 0:00:00
GTC # #	Go to title and chapter number	3 0:00:00
GTM #####	Go to time hhmmss	3 0:03:43